

Premier Acoustic Product Datasheet



Model: JPA-1060 / JPA-1120



Description

Freestanding mixer amplifier available in a choice of 60 watt and 120 watt outputs.

Integral module slot enables a dedicated tuner, cassette player, tuner/cassette, CD player, tuner/CD player or digital message module to be fitted.

Optional 3U rack shelf available (**RMK-10A**)

- Front mounted mic socket with vox priority over other inputs.
- Four further audio inputs, each with individual attenuation (three switchable between mic/line level and the fourth switchable between line/phono level).
- Three 100-volt line speaker output zones with individual selection switches.
- Low impedance direct output
- Bass and treble controls.
- Output level LED meter.
- Remote chime connections - can be operated by pushing the button on the front of the amp or by a closing contact on the paging microphone.
- Telephone interface connections.
- 120/220/230/240 volt AC or 24 volt DC operation.

Specification

Model Number:	JPA1060	JPA1120
Rated output (RMS)	60w	120w
Output impedance	70V, 100V, 8Ω & 4Ω	
THD @ 1kHz	Less than 1% (1kHz)	
Equalizer	Bass: ± 10dB @ 100Hz Treble: ± 10db @ 10Hz	
Frequency response (±3dB)	80Hz~15kHz	
Signal to noise ratio	Line: Better than 70dB, Mic: Better than 60dB	
Input	Mic 1~4: 3mV, Line: 300mV, Phono: 2.4mV	
Weight (kg)	10	12
Dimensions (W x H x D) mm	420 x 110 x 320	
Power requirement	120V/220V/230V/240V AC 50/60Hz or 24V DC	