

Premier Acoustic Product Datasheet



Model: JCR-10

Description



Cassette/tuner module suitable for use with Jedia mixer amplifiers.

Tuner has digital tuning with FM/AM coverage and 18 memory presets.

Cassette player has auto reverse with LED direction indicators.

Specification

Cassette Section

Signal to Noise Ratio	60 dB
Wow & Flutter	Less than 0.35%
Frequency Response	100Hz-6.3KHz (± 3 dB)
Tape 'FF' or 'REW'	About 180 seconds
Tape speed	4.76cm/sec
Dimensions (height x width x depth)	40mm x 194mm x 213mm
Overall Weight (inc. packaging)	1.5Kg

Tuner Section

Tuning Range	FM 87.5MHz to 108 MHz AM 522MHZ – 1620MHz
Antenna Input	FM: 300ohm balanced or 75ohm unbalanced AM: High impedance lead antenna
Usable Sensitivity	FM: 2 μ V / AM: 4.5 μ V
Signal to Noise Ratio	FM: 60dB / AM: 45dB

Premier Acoustic Ltd, Unit 9, Sedgley Trading Estate, Sedgley Park,
Prestwich, Manchester M25 9WS

Tel: 0161 798 6336 Fax: 0161 798 6226

JCR-10 Page 1 of 1