

# Premier Acoustic Product Datasheet



**Model: JTP-10**

## Description



Tuner module with digital tuning, suitable for use with Jedia mixer amplifiers.

FM/AM coverage with 18 memory presets.

## Specification

|                                     |  |
|-------------------------------------|--|
| Tuning Range                        | FM 87.5MHz to 108 MHz<br>AM 522MHz – 1620MHz                               |
| Antenna Input                       | FM: 300ohm balanced or 75ohm unbalanced<br>AM: High impedance lead antenna |
| Usable Sensitivity                  | FM: 2 $\mu$ V / AM: 4.5 $\mu$ V  |
| Signal to Noise Ratio               | FM: 60dB / AM: 45dB  |
| Dimensions (height x width x depth) | 40mm x 194mm x 120mm   |
| Weight (inc. packaging)             | 0.8kg  |

Premier Acoustic Ltd, Unit 9, Sedgley Trading Estate, Sedgley Park,  
Prestwich, Manchester M25 9WS

Tel: 0161 798 6336 Fax: 0161 798 6226

JTP-10 Page 1 of 1