

Premier Acoustic Product Datasheet



Model: JTU-110B AM/FM TUNER



Description

FM/AM rack mounting tuner

18 FM presets & 12 AM presets
with Scan and Seek Functions

Large LCD Digital Display

Auto store memory function (A/PS)

Signal strength meter

Balanced mono XLR Output

Unbalanced stereo RCA Output

AC and DC 24V operation

Specification

Tuning range	FM 87.5 ~ 108MHz	AM 522 ~ 1620kHz
ANT Input	FM: 300ohm balanced or 75ohm unbalanced AM: Loop antenna and lead antenna	
Usable sensitivity	FM: 2 μ V	AM: 4.5 μ V
Signal to noise ratio	FM: 60dB	AM: 45dB
Memory Back-up	For 45 days (After AC Power Off)	
Output Level	0.245 (-10dBm) Unbalanced	
Variable output	0.775V (0dBm) Balanced	
Fixed output		
Power consumption	7.3W	
Power source	120V/220V/230V/240VAC 50/60Hz, 24VDC	
Dimensions (mm)	483mm(W) x 44mm(H) x 120mm(D)	
Weight	3.2 kg	